

## AMPL



## DESCRIPTION

- ▶ Specifically designed for marked and unmarked vehicles, the AMPL™ module allows effective control of all accessories required in any emergency situation.
- ▶ Ideal for controlling accessories such as lightbars, sirens, light modules, traffic advisors, gun lock mechanisms, etc.

## FEATURES

- ▶ 8 independant outputs for lightbar or emergency light control
- ▶ 7 dedicated blackout relays (front and rear lamps)
- ▶ 9 selectable tones siren output (100 or 200 Watts)
- ▶ Front and rear Wig-Wag outputs (Programmable speed and flash pattern, no external device required)
- ▶ Programmable gun lock activation output
- ▶ Siren control transferable to horn activation switch
- ▶ PA microphone input (only comptabile with Zone Technologies' MIC-M microphone)
- ▶ Programmable timers
- ▶ Programming from the keypad



## ELECTRICAL SPECIFICATIONS

<b>Operating Voltage:</b>	10 to 16Vdc
<b>Operating Temperature:</b>	-40°C to 75°C (-40°F to 167°F)
<b>Current draw:</b>	Standby, no ignition: 1mA Activated (no load), with ignition: 350mA
<b>Available outputs:</b>	
- Lightbar	8 outputs ..... 10A (each)
- Front Wig-Wag:	2 outputs ..... 30A (each)
- Rear Wig-Wag:	2 outputs ..... 10A (each)
- Blackout (head lamps):	1 output ..... 30A
- Blackout (remaining lamps):	6 outputs ..... 10A (each)

## AVAILABLE KEYPADS

24 Keys



(police keys shown)

10 Keys



## PRODUCT NUMBERS

Number*	Description
AMPL10-2-0800	POLICE SYSTEM WITH KEYPAD CABLE (20 FEET)
AMPL10-D-0800	POLICE SYSTEM WITH 10 KEYS KEYPAD, FUSES & HIGH POWER HARNES
AMPL24-K-Z510	ZONE MARKED SYSTEM WITH 17 KEYS KEYPAD
AMPL34-M-Z510	POLICE SYSTEM WITH SLIDE, FUSES, P.A. & HARNESS HP

\* The last digits represent the membrane number. See the membrane section (p. 102) for more information.