# ProSigna1™

# DIAMONDBACK MINIBAR



#### DESCRIPTION

- ▶ Fully waterproof and vibration resistant, the Diamondback<sup>™</sup> Minibar is ideal for anyone on a budget who doesn't want to compromise on quality and power.
- ▶ The Diamondback Minibar design offers superior 360<sup>0</sup> output that meets SAE J845 Class 1 standards.

#### **FEATURES**

- Multi-voltage input: 12 to 24Vdc
- >23 selectable flash patterns
- High intensity LED modules (24 LED modules of 1 Watt)
- LEDs rated to 100 000 hours of operation
- Non-volatile memory recalls last flash pattern used at power up
- > Weatherproof and vibration resistant design for internal or external use
- Available in permanent or magnetic mount
- Reverse polarity protection
- Multiple units can be synchronized
- 🕨 Color available: 🦰 🛑



# **ELECTRICAL SPECIFICATIONS**

Operating Voltage:	12 to 24Vdc
Maximum Current:	3.8A at 12Vdc / 1.9A at 24Vdc
Average Power:	22.8 Watts (varies with pattern)
Maximum Power:	45.6 Watts
Fuse Recommended:	6A


\*Consumption in Steady-On mode.


## **CONNECTING OPTIONS**





#### DIMENSIONS







## **PRODUCT NUMBERS**

Number	Description
73003Z	PROSIGNAL - DIAMONDBACK - PERMANENT/MT 12-24VDC - AMBER
73103Z	PROSIGNAL - DIAMONDBACK - MAGNETIC/MT 12-24VDC - AMBER
73105Z	PROSIGNAL - DIAMONDBACK - MAGNETIC/MT 12-24VDC - BLUE
73000Z	PROSIGNAL DIAMONDBACK - 2 X MOUNTING BRACKET KIT
78001Z	PROSIGNAL DIAMONDBACK - 2 X MAGNETIC 7" SUCTION CUP KIT